

LTECH



LTECH USB-DMX controller LT512



LT-512

Input Voltage	5V DC
Power Consumption	<2W
Connection	Mini USB
Internal Memory	120 steps
Channel Output Connector	512 XLR-3
Transmission Signal	DMX512
PC Software	LTECH LED player
Working Temperature	-30°C~65°C
Package Size	L140×W200×H52mm
Weight(G.W.)	330g

Auto Generated Effects
Creates some effect buttons and curves for each new show.

Groups + Sub-Groups
Easy and full feature selection.

Multiple Tabs + buttons
It is possible to create an unlimited number of tabs and buttons to organize your show and maximize your live performances impact.

DMX + MIDI external Controls
Triggers + controls via MIDI devices and DMX console.

Audio Triggers
Takes the Beat and level of music for scenes, steps, channels and faders.

Fading tool
For Theatre and Live: Fade in + Fade Out time + Delay + list of scenes.

XY + Color Effect generator
Create complex shape movements and color sequences easily.

Layer Mask
Change color DMX inputs in all your scene rapidly with only 1 action.

Matrix + Pixel Mapping
Easy graphic configuration.

Art-Net output signal
Up to 328 addresses management, maximum. Output signal from 10/100 computer network card.

Timeline options
Play, Pause, Stop, Jump to: Marker, Audio, repeat project, Time Zoom and scrolling.

Marker points
Add Marker points anywhere in time.

Audio and Video Timeline
Unlimited timeline in minutes for lighting + 1 Audio Line + 1 Video Line.

30 mn to 24h Timeline
20 minutes max. with a 1 tab DMX connected, 24 hours with a NET512 or NET32 connected.

Scene Blocks
Easy and quick scene block creation for Audio Play Remote control.

Video Player
Any movie file of format: MP4, AVI, MOV, WMV, FLV, 3GP, etc. is supported.

Entertainment, Live, Sound, Lights, Theater, DJ's

LTECH

Lighting and Visual Control Solutions - Pro DMX